

# DIGITALLY CONTROLLED FM RADIO

Component: MK194



### Features

- HQ FM receiver module with excellent sensitivity
- single button station search function
- 4 station presets with confirmation beep
- restore of last selected station at switch-on
- soft fade-in of last audio level at switch-on

### Specifications

- FM range: 88-107.9MHz (0.1MHz step)
- power supply: 9VDC (battery not incl.)
- power consumption: 40mA max.
- dimensions: 130 x 85 x 45mm / 5.1 x 3.34 x 1.8"

